


**MADE IN AMERICA**

## BUILD YOUR OWN OUTDOOR SIGN LIGHT



This sign unit provides high light levels with even distribution, for spot lighting. The unit is weather resistant and suitable for outdoor applications.

**DIMENSIONS:**



| Fixture Length |  |
|----------------|--|
| 53"            |  |
| 101"           |  |

### BUILD YOUR OWN OUTDOOR SIGN LIGHT PRODUCT FEATURES

|                           |  |
|---------------------------|--|
| <b>WATTAGES</b>           | <b>Magnilumen Plus High Output:</b><br>4ft- 60W; 8ft- 120W   |
| <b>COLOR TEMPS</b>        | <b>Magnilumen Plus High Output:</b><br>40K, 50K  |
| <b>LUMENS</b>             | See lumens chart   |
| <b>INPUT VOLTAGE</b>      | 120/277V   |
| <b>LED LIFESPAN (L70)</b> | <b>Magnilumen Plus High Output:</b> 50,000 hours   |
| <b>MOUNTING</b>           | Units are designed to be conduit mounted either individually, tandem, or in a continuous run.  |
| <b>CONSTRUCTION</b>       | Housing is made of heavy gauge extruded aluminum with die cast end plates and splice box fittings. Housing interior is finished in a baked enamel finish for maximum reflectivity and durability. Splice box is threaded for 3/4" conduit and contains adjusting screws for housing. Lens is clear smooth slide-on acrylic that resists yellowing. |
| <b>ELECTRICAL</b>         | Housing is UL Certified damp and wet location.   |
| <b>QUANTITY OF BARS</b>   | 4ft- 1; 8ft- 2   |
| <b>LISTED</b>             | UL Certified for wet location on housing only ETL- Light engine only   |
| <b>WARRANTY</b>           | 5 year   |



### HIGH OUTPUT PRODUCT BUILDER

| PRODUCT # | SIZE           | COLOR TEMP | # OF BARS            | BAR LENS               | WATTAGE                   |
|-----------|----------------|------------|----------------------|------------------------|---------------------------|
| ZL-OD-LED | - [ ] -        | - [ ] -    | - [ ] -              | - [ ] -                | - [ ]                     |
|           | 4=4FT<br>8=8FT | 40K<br>50K | 4ft<br>1<br>8ft<br>2 | CL=Clear<br>Blank=None | 4ft<br>60W<br>8ft<br>120W |



## BUILD YOUR OWN OUTDOOR SIGN LIGHT

### LUMENS

| Wattage 4ft = 1x 60W Driver        | Wattage | Lumens With Lens | Lumens Without Lens |
|------------------------------------|---------|------------------|---------------------|
| Driver Settings Below 1x60W Driver |         | 165              | 175                 |
| <b>62 Watts</b>                    | 62      | 10,230           | 10,850              |
| <b>60 Watts</b>                    | 60      | 9,900            | 10,500              |
| <b>57 Watts</b>                    | 57      | 9,405            | 9,975               |
| <b>55 Watts</b>                    | 55      | 9,075            | 9,625               |
| <b>50 Watts</b>                    | 50      | 8,250            | 8,750               |
| <b>45 Watts</b>                    | 45      | 7,425            | 7,875               |
| <b>40 Watts</b>                    | 40      | 6,600            | 7,000               |

| Wattage 8ft = 2x60W Drivers         | Wattage | Lumens With Lens | Lumens Without Lens |
|-------------------------------------|---------|------------------|---------------------|
| Drivers Settings Below 2x60W Driver |         | 165              | 175                 |
| <b>124 Watts 2x62W Drivers</b>      | 124     | 20,460           | 21,700              |
| <b>120 Watts 2x 60W Drivers</b>     | 120     | 19,800           | 21,000              |
| <b>114 Watts 2x 57W Drivers</b>     | 114     | 18,810           | 19,950              |
| <b>110 Watts 2x55 Watt Drivers</b>  | 110     | 18,150           | 19,250              |
| <b>100 Watt 2x50 Watt Drivers</b>   | 100     | 16,500           | 17,500              |
| <b>90 Watts 2x45 Watt Drivers</b>   | 90      | 18,150           | 15,750              |
| <b>80 Watts 2x40 Watt Drivers</b>   | 80      | 13,200           | 14,000              |